

BULBRITE

LED TURBO MR16s



Transformer Compatibility List

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment.

Actual results may vary.

Turbo LED MR16s are compatible with all non-dimmable magnetic low voltage transformers. These lamps are also compatible with select electronic low voltage transformers. Below is a list of popular low voltage electronic transformers that have been tested for compatibility with the following Turbo LED MR16s:

- LED6MR16WW/FL
- LED6MR16WW/NF
- LED6MR16DL/FL

Please contact us for more information.

ELECTRONIC TRANSFORMERS				Number of MR16s per transformer					
Brand	Model	Power Rating (W)	Input Voltage	1	2	3	4	5	6
Elco	ET526	50	120V	Y	Y	N	N	N	N
Hatch	RS12-60M	60	120V	Y	Y	Y	Y	Y	Y
	VS-12-60WNW	60	120V	Y	Y	Y	Y	Y	Y
	VS-12-60WD	60	120V	Y	Y	Y	Y	Y	Y
	RS12-80M	80	120V	Y	Y	Y	Y	Y	Y
Jesco	LV104-50	50	120V	Y	Y	Y	Y	Y	Y
Juno	R731BL	50	120V	Y	Y	Y	Y	Y	Y
Ligtech	LET-60	60	120V	N	N	N	N	N	N
	LET-75	75	120V	N	N	N	N	N	N
WAC	HHT-802-BK	50	120V	Y	Y	Y	Y	Y	Y
	EN-1260-R-AR	60	120V	Y	Y	Y	Y	Y	N
	EN-1275-R-AR	75	120V	Y	Y	Y	N	N	N
	EN-12100-R-AR	100	120V	Y	Y	Y	Y	Y	Y

Y - Compatible

N - Not Compatible

Contact Information:

Bulbrite Industries Inc.
 145 W. Commercial Ave.
 Moonachie, NJ 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708

©2011 Bulbrite Industries Inc.

All Rights Reserved.

www.bulbrite.com/LED

BULBRITE

LED Retrofit Lamps

Transformer Compatibility List



PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

6.5W LED MR16

Model: LED6MR16WW/D

ELECTRONIC TRANSFORMERS				Number of Lamps				
Brand	Model	Power Rating (W)	Input Voltage (VAC)	1	2	3	4	5
Elco	ET526*	50	120V	P	N/A	N/A	N/A	N/A
Hatch	RS12-60M-LED	60	120V	P	P	P	P	P
	RS12-30M -LED	30	120V	P	P	P	P	N/A
	RS-12-15M-LED	15	120V	P	P	N/A	N/A	N/A
	RS12-60M	60	120V	F	F	P	P	P
	RS12-80M	80	120V	NR	F	F	P	P
	VS-12-60WD	60	120V	F	F	F	P	P
Jesco	LV104-50*	50	120V	F	N/A	N/A	N/A	N/A
Juno	R731BL*	50	120V	P	N/A	N/A	N/A	N/A
	T537	75	120V	F	F	F	P	P
Lightech	LET-60	60	120V	NR	P	P	P	P
	LET-75	75	120V	F	F	F	P	P
WAC	HHT-802-BK*	50	120V	NR	N/A	N/A	N/A	N/A
	EN-1260-R-AR	60	120V	NR	F	P	P	P
	EN-1275-R-AR	75	120V	NR	F	P	P	P
	EN-12100-R-AR	100	120V	P	P	P	P	P
Solution	Net 1075	80	120V	P	P	P	P	P
MAGNETIC TRANSFORMERS††				Number of Lamps				
Brand	Model	Power Rating (W)	Input Voltage (VAC)	1	2	3	4	5
Generic	Generic	300	120V	P	P	P	P	P

* Track head with built-in transformer for a single lamp.

†† Test results based on 1 standard magnetic transformer. Performance may vary by model and brand.

Not Compatible

Compatible

P - Pass - Stable light output, no sign of flicker, no audible noise

F - Flicker - Flickering was observed during testing when the transformer was used with the number of lamps specified above

NR - Not Recommended - Abnormal voltage

N/A - Not Applicable - Does not apply to track head or the number of lamps exceeds transformer recommended power

Contact Information:

Bulbrite Industries Inc.
145 W. Commercial Ave.
Moonachie, NJ 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708

©2012 Bulbrite Industries Inc.

All Rights Reserved.

www.bulbrite.com/LED